

AMENDMENTS TO THE CLAIMS:

Kindly amend claims 1-3, 7, 10-11, 13, 15 and 18-21, as shown below.

This listing of claims will replace all prior versions and listings of claims in the
Application:

Claim 1 (currently amended): A device for measuring dispersion of a link between two
switching nodes of an optical network comprising:

a phase measuring unit for determining a first phase of a data signal received over said
link on a first wavelength $\lambda 1$ and a second phase of said data signal received over said link on a
second wavelength $\lambda 2$; and

a dispersion measurement controller for controlling operation of said phase measuring
unit, and ~~characterizing~~ determining the dispersion of said link at a wavelength of interest
 $\lambda = (\lambda 1 + \lambda 2)/2$ based on said first and second phases.

Claim 2 (currently amended): A device as claimed in claim 1, wherein said phase measuring
unit comprises:

a test dividing circuit for $[[1:n]]$ dividing a first and a second test clock extracted from
said data signal received on said first and second wavelength, respectively, and providing a first
and a second divided test clock;

means for determining a first and a second rotation signal indicative of the digital offset
between said first and second divided test clocks with a respective frame start; and

a phase detector for measuring the phase of said first and second divided test clock with
respect to a static reference to obtain said first and said second phases.

HAYES SOLOWAY P.C.
130 W. CUSHING ST.
TUCSON, AZ 85701
TEL. 520.882.7623
FAX. 520.882.7643

175 CANAL STREET
MANCHESTER, NH 03101
TEL. 603.668.1400
FAX. 603.668.8567

Claim 3 (currently amended): A device as claimed in claim 2 further comprising a reference dividing circuit for $[[1:n]]$ dividing a reference clock extracted from said data signal received on a reference wavelength and providing a divided reference clock, wherein said static reference is provided by said divided reference clock.

Claim 4 (original): A device as claimed in claim 2, wherein said means for determining is a frame detector.

Claim 5 (original): A device as claimed in claim 2, wherein said phase measuring unit further comprises an analog-to-digital converter for providing said first and said second phases to said dispersion measurement controller in a digital format.

Claim 6 (original): A device as claimed in claim 3, further comprising:

a reference receiver for detecting said data signal received on said reference wavelength and extracting said reference clock;

a test receiver for detecting said data signal received on said first and second test wavelengths and extracting said first and second test clocks; and

a dispersion measuring card for accommodating said phase measuring unit and said receivers,

wherein each said receiver is provided with means for serial-to-parallel converting said data signal and providing same to said means for determining.

Claim 7 (currently amended): A device as claimed in claim $[[5]]$ 6, further comprising, on said card, a reference transmitter for modulating said data signal received over said reference wavelength and transmitting same to the node at the input of said link.

Claim 8 (original): A device as claimed in claim 1, further comprising a memory for storing dispersion calibration data for said phase measuring unit.

Claim 9 (original): A device as claimed in claim 8, wherein said memory further stores dispersion data calculated for said link.

Claim 10 (currently amended): A method for characterizing the dispersion of a link of an optical network comprising:

(a) transmitting over said link a data signal over a first test wavelength λ_1 and thereafter over a second test wavelength λ_2 ;

(b) at the output of said link, measuring a first phase of said data signal received on said first wavelength λ_1 and a second phase of said data signal received on said second wavelength λ_2 ; and

(c) ~~characterizing~~ determining the dispersion of said link at a wavelength of interest $\lambda = (\lambda_1 + \lambda_2)/2$ based on the difference between said first and second phases.

Claim 11 (currently amended): A method as claimed in claim 10 wherein said step (b) comprises:

[[1:n]] dividing a first and a second test clock extracted from said data signal received on said first and second test wavelengths, and providing a first and a second divided test clocks; and comparing the phase of said first and second divided test clocks with a static reference to obtain said first and said second phases.

Claim 12 (original): A method as claimed in claim 11, further comprising determining a first and a second rotation signal indicative of the time offset between said data signal received over said respective first and second wavelength.

Claim 13 (currently amended): A method as claimed in claim 12, wherein step of determining a first and a second rotation signal comprises:

serial-to-parallel converting said data signal received over said respective first and second wavelength to obtain a respective ~~n-bit~~ test word;

determining said first and said second rotation signal as the digital offset between said respective first and second divided test clock and the respective frame start.

Claim 14 (original): A method as claimed in claim 11, wherein said static reference is provided by said data signal received on a reference wavelength λ_{ref} , transmitted continuously over said link and synchronous with said λ_1 and λ_2 .

Claim 15 (currently amended): A method as claimed in claim 11, wherein said step (c) comprises:

determining, from said first phase and said first rotation signal, a phase signal *phase_1*, indicative of the phase of said data signal when carried by said first test wavelength; and

determining, from said second phase and said second rotation signal, a phase signal *phase_2*, indicative of the phase of said data signal when carried by said ~~first~~ second test wavelength.

Claim 16 (original): A method as claimed in claim 15, further comprising calculating the dispersion parameter for said link at said wavelength λ as:

$$D(\lambda) = \frac{(phase_2 - phase_1)}{\lambda_2 - \lambda_1} \cdot \frac{1}{L},$$

wherein L is the length of said link.

Claim 17 (original): A method as claimed in claim 16, further comprising calculating the dispersion slope $S(\lambda)$.

Claim 18 (currently amended): A method as claimed in claim 10, further comprising repeating steps (a) ~~to~~ (c) for a plurality of first and second wavelengths pairs for determining the dispersion parameter and slope across the entire spectrum used in said network to obtain a link dispersion profile.

Claim 19 (currently amended): A method as claimed in claim ~~10~~ 18, further comprising storing said dispersion profile in a database.

Claim 20 (currently amended): A method as claimed in claim ~~10~~ 18, further comprising using said link dispersion profile for optimizing dispersion of said link.

Claim 21 (currently amended): A method as claimed in claim 10, further comprising repeating steps (a) to (c) by switching between said first and second wavelengths to obtain a plurality of measurements for all $[2\pi/n]$ phases of said test clock, to calibrate the dispersion measurements for a particular configuration of said link.